

User Guide



Absolute Stream



THANK YOU!

Congratulations on purchasing the **Absolute Stream**, reportedly one of the best-sounding music servers currently available.

If you are already an Ideon owner, thank you for your continued trust in our approach to music reproduction and we hope you will soon enjoy the absolute Suite (if you aren't already doing so!).

If you are a newcomer, we are thrilled to welcome you on board our **Absolute Suite**!

Your **Absolute Stream** is an audiophile music server; it was designed from the ground up to offer superlative sound, surpassing the sonics of the best commercially available streamers. To achieve this, we equipped the **Absolute Stream** circuit with several audiophile features, components, and proprietary circuits:

- Proprietary re-clocking platform: it uses a hi-quality femto clock and is fully upgradable;
- Seriously over-engineered power supply:
 - Proprietary, ultra-low esr, special bypass power filter improving the transient current for the CPU (spectacular sound improvement!)
 - Huge main caps using low esr, audiophile silk capacitors

- ◊ hand-made audiophile transformer
- Proprietary, "no-noise", rectification active bridge topology which eliminates noise from diodes
- Short signal paths without wiring
- Audiophile design & solid aluminium construction
- Simplified, bare-bones operation avoids internal noise-inducing circuits


The **Absolute Stream** is first device in the Absolute Suite, the superlative audiophile digital front end comprising the **Absolute Stream**, the **Absolute Time**, and the **Absolute** (DAC).



© Ideon Audio, August 2020 – absolute stream manual v.1 Due to continuous research, Ideon Audio reserves the right to change specifications without notice.



Connecting



Setting up your Absolute Stream is simple, using it is even simpler.

Hardware

Please make the connections below in the order presented. Power cable connected in the end.

Signal inputs: in the middle of the back plate you will see three (3) inputs marked LAN, HD1, HD2. Please connect your network's LAN cable to the corresponding input.

If you have libraries stored on USB external discs, please connect to HD1, HD2 as applicable. You can use a NAS as well.

audio ports		LAN	HDI	HD2	handcrafted in Athens, Greece	
		US	SB Hard D	isks (music))	
Out to DAC	LAN cor				, ,	

On the left side on the back plate you will see two USB "audio out" connections which connect to the DAC:

- On the right you have signal with 5V bus
- On the left is pure signal; unless your
- DAC needs 5V supply, this is by far the recommended output

The output connects to your DAC. We recommend you use good quality USB cable.

For Ideon owners, the output connects to the signal re-clocker (absolute Time, Master Time, 3R).

Finally, connect the power cord to the IEC input on the right side of the back plate. Ensure it is safely inserted in the right. Press the knob to <u>s</u>witching the device to stand-by mode.

Absolute Stream: rendering your music.

Important Notice

The Absolute Stream, above all is a highly sophisticated renderer which you can use with any music player program (client) that supports UPNP (most of the well-known commercial of freeware do that), such as Roon, JRiver, Audiorvana, Foobar, and similar. The rendering of music is done with the highest standards of our designs and we make sure it is happening in the server, so no loss of sound quality is possible!

Additionally, we provide a music player program along with the device, providing all the functionality of such a program. You can experiment with this music player program or, alternatively, use the one that you prefer and around which you have built your music library.

Your Music's metadata

Important Notice

Your music files need to contain the right metadata. There is a minimum of data that must be in the file so the system can recognize, find, , display, and provide information relating to any file at the very least, a proper title, artist and album name. The more metadata you have the better, but if your tracks lack the minimum required data in order to be read, then these files won't be searchable and won't appear in any search or indexing process. They will be in your database, but the system will not be able to retrieve them!

Software – GUI

Press the power button on the front plate (off center left) to power up the Absolute Stream.

You are now ready to connect!

- Connect to your router, go to "network", then "LAN";
- On the screen you will see all the connected devices in your network including Ideon, and their associated IP addresses.
- Note and copy the IP address your router has assigned to **ideon** (it should look like 192.168.X.Y)

Now you need to choose a device to control your Ideon streamer - tablet, laptop, phone, etc. Any device with a browser will do. We designed the application this way for simplicity and ease of use.

Open the device browser, type in the IP address your router assigned to Ideon, and press enter. This will launch the Ideon Audio application



© Ideon Audio, August 2020 – absolute stream manual v.1

Settings

Invest a moment to carefully complete the settings, they only need to be done once!

A series of dialogue boxes will appear, the first being language & skin color choice.

The **next** screen is "Your NAS settings", important if your **music** is in a **NAS STORAGE!**


Audio NAS Streaming Update X		Your NAS Settings				
Your NAS Settings		Select type	Samba A (guest access)			
Select type	None (not applicable)	NAS IP address	NAS IP address			
Changes here will cause a system reboot	None (not applicable) Samba A (guest access)	Path	Music folder path in NAS (e.g. /music)			
	Samba B (access with credentials) NFS	Select samba version	\$.0			
Your NAS Settings		Your NAS Settings				
Select type	Samba B (access with credentials)	Select type	Samba B (access with credentials)			
NAS IP address	NAS IP address	NAS IP address	NAS IP address			
Path	Music folder path in NAS (e.g. /music)	Path	Music folder path in NAS (e.g. /music)			
Select samba version	3.0 \$	Select samba version	3.0 +			
Username	Username	Username	Username			
Password	Password	Password	Password			

• Select type:

- select "samba A" if a guest (such as a friend) is accessing your NAS or your accessing a NAS without credentials
- ◊ select "**samba B**" if you are accessing a NAS with credentials (username & password)
- NAS IP address: enter your NAS IP address or its name
- Path: enter the NAS path to your music
- Username / password (only applicable if you have selected "samba B"): enter the appropriate your credentials
- Press next

The following screen is **Operating Info**. We recommend you save the information in this screen for future reference.

Clicking **submit** completes the first part of the set-up!



Create your music library and play music.


Clicking on **Submit** takes you to the "**Playing now**" screen. **This is the application's main** screen for playing music.

It's time to **CREATE your MUSIC library**! Follow the following simple steps:

Click on **Ideon Audio app** main menu icon ("main menu") on the top left of your screen. From the drop-down menu select: Create/Update library and then **Update library**. The app will start indexing your library. Please wait until the indexing is complete.

Click on "close" and you are ready to go!

Now the playing screen will look like this:



The left half is the playing window (i.e. what is playing at any time) while the right side contains albums of your library. The first 100 will appear. The default sorting is Album Artist.

You can, of course, opt for a different sorting using the icon to the right of the search field.

Top right shows your library metrics (tracks, time, etc)

The screen bottom has the **app's** four basic **functions**:

- **Playing now** (i.e. what is playing, from which file, album, artist, etc)
- Library (your music library portrayed as a data base or as a file system)
- **Queue** (i.e. what you have selected to listen to you can save this as a "playing list")
- **Search** (self-explanatory; using keywords and any parameter)



© Ideon Audio, August 2020 – absolute stream manual v.1

Playing Now (how to play music)

We are at the **Playing now** screen (see upper left). This can be selected from the main bar of the application at the bottom of the screen. This, along with the Queue option will be your main screens, depending on how you want to play music.

Clicking on the album of your choice (right side) the album will expand to reveal the tracks. Click on a track for instant play.


On the left side you will see the artwork (if available) of the track being played as well as relevant information. A pause/play control and progress bar appear below the artwork.

The four tracks that follow what is currently playing, "Next in queue", are also listed below. (The list is empty if there are none.)

Clicking on any of the listed tracks, immediately loads it to the player, replacing the current one.


The player's **main controls** are top bar right (i.e. previous, stop, pause/play, next, output volume).

Expanding an album



Clicking on a folder artwork (i.e. an album) immediately reveals its tracks.

Clicking on the album **title** opens four options:



Play album: immediately loads and plays the album

Add to queue: adds all of the chosen album's tracks to the end of the current queue.

Replace queue: erases the current queue and replaces its contents with all the tracks from the current album

Add to playlist: choose a playlist -- or create a new one -- to which all contents of the current album are added

Selecting and playing specific tracks

Expand the album. Clicking on the mini menu on the right side of each track opens five options:



Play: as stated

Add to queue: add the track to the end of the current queue

Add after current playing song: will play selected track after the current one is complete

Replace queue: erases the current queue

and replaces its contents with the selected track

Add to playlist: choose a playlist -- or create a new one -- to which the selected track will be added

Song details: reveals data about the specific track (provided there are data attached to the chosen track)



© Ideon Audio, August 2020 – absolute stream manual v.1

Searching and Sorting Your Albums

On the right side of the screen you will find the search bar and the sorting button

Search: enter any key word in the search bar; the search function will display all the artwork containing your key word (or characters). Clicking on the magnifying glass allows you to focus the search – our suggestion is to use *albumartist*

Sorting menu: you will find this immediately following the search bar. This menu controls how you wish to sort your albums. Again, our suggestion is *albumartist*




View: the button of the far right (two arrows) is a toggle switch alternating between thumbnails and list view for your albums

Left Pane – Playing Now – the Information Icon

Clicking on the gear icon in the upper middle of the screen allows you to choose track information on the track being played. This information appears on the left pane below the track title (pic).

To the left of this gear, you have the thumbs **up** & thumbs **down** buttons, as well as the "**+add** to playlist" button.



Queue (your listening tracks queue)

You are at the **Queue** screen (see upper left). This can be selected from the main bar of the application at the bottom of the screen. Here you can see all the tracks that have been selected to be played in queue. Remember that when browsing tracks or albums you always have the choice to add them to your Queue.

At the upper left of the screen you have two options. The default is the Queue, where you see all tracks of the current Queue.

in I	👻 🚺 Artur Pizar	rro - Sonata No. 8 'Pathétique' in (C minor Op. 13 Grave; Allegro di i	molto e con brio	H B P H	•
Queue	Last played				15 Songs – 2 Hrs 07 M	in 45 Sec
8	🛠 💽 🔳 🔍 🔍 Any Tag 👻 Search queue					
#	Title		Artist	Album	Duratio	n ¢
1	"Songs my mother taught me" from Gypsy melodies, op.55, no	5.4	Yo-Yo Ma, Patricia Zander	The Dvorak Ablum	2:55	=
2	Concerto For Violin, Cello And Orchestra In A Minor Op. 102		Anne-Sophie Mutter	Brahms: Violin Concerto / Double Concerto (Mutte	r) 22:08	=
3	Concerto For Violin, Cello And Orchestra In A Minor Op. 102		Anne-Sophie Mutter	Brahms: Violin Concerto / Double Concerto (Mutte	r) 9:42	=
4	Tragic Overture Op. 81		Anne-Sophie Mutter	Brahms: Violin Concerto / Double Concerto (Mutte	r) 18:04	=
5	Tragic Overture Op. 81		Anne-Sophie Mutter	Brahms: Violin Concerto / Double Concerto (Mutte	r) 7:30	≡
6	Concerto For Violin, Cello And Orchestra In A Minor Op. 102		Anne-Sophie Mutter	Brahms: Violin Concerto / Double Concerto (Mutte	r) 8:42	≡
7	Concerto For Violin, Cello And Orchestra In A Minor Op. 102		Anne-Sophie Mutter	Brahms: Violin Concerto / Double Concerto (Mutte	r) 9:42	=
8	The Shadow of Your Smile		Archie Shepp	Archie Shepp: True Ballads	9:53	=
9	La Rosita		Archie Shepp	Archie Shepp: True Ballads	8:14	=
		🗊 Queue 15	۵		Q Search	

At the right side of the screen you see the number of tracks and total playing time of the current Queue.

By clicking on Last Played, you see the most recently played tracks

The track currently playing is highlighted; duration and remaining time are also visible

You can play instantly any track in the Queue by just clicking on it.

For every track on the Queue there is a menu icon (three parallel lines) at the far right of the track's line.

5 5 6	Tragic Overture Op. 81 Concerto For Violin, Cello And Orchestra In A Minor Op. 102	Anne-Sophie Mutter Anne-Sophie Mutter	Brahms: Violin Concerto / Double Concerto (Mi Brahms: Violin Concerto / Double Concerto (Mi	Remove Remove all upwards Remove all downwards	
7	Concerto For Violin, Cello And Orchestra In A Minor Op. 102 The Shadow of Your Smile	Anne-Sophie Mutter	Brahms: Violin Concerto / Double Concerto (Mu Archie Shepp: True Ballads	Add to playlist Song details	`
9	La Rosita	Archie Shepp	Archie Shepp: True Ballads	8:14	T
10	What a Difference a Day Made	Aretha Franklin	Aretha Sings the Blues	3:31 =	ł.

10



© Ideon Audio, August 2020 – absolute stream manual v.1

Clicking on this menu for any particular track in the Queue opens five options:

Remove: immediately removes the track from the Queue.

Remove all upwards: removes from the Queue all tracks above the track.

Remove all downwards: removes from the Queue all tracks below the track.

Add to playlist: adds the track in question to a playlist

Song details: reveals data about the specific track (provided there are data attached to the chosen track)

Queue options

At the top of the Queue screen you have four icons and a search bar performing the following actions in your Queue:

Queue	Last played			15 Songs – 2 Hrs 07 Min 45 Sec
	X 🖸 🔎 🖛 🔹 Q Any Tag × Search queue			
	Title	Artist	Album	Duration 🌣

Save Queue icon (diskette icon): saves your Queue as a playlist.

Shuffle Queue icon (crossed arrows icon): shuffles your Queue anytime you click on this icon Add to queue icon (little screen with + sign icon): adds randomly user selected number of tracks or albums to the Queue

Clear queue / keep current song icon (three lines icon): you have the option to clear the whole Queue or to just keep the current playing song


Searching the Queue

Using the search bar on the top of the screen, you can search within the current Queue. By default, the system searches any tag with the keyword entered. You can use the Search meny (magnifying glass icon) to select the field you want to search with a keyword, i.e. searching Filenames, Albums, Albumartists, Artists, Genre or Titles

Library

You are at the **Library** screen (see upper left). This can be selected from the main bar of the application at the bottom of the screen. Here, you can have different views of your Music Library, Playlists and Filesystem.

Artwork view is shown below



List view is shown below

Classic FM Guitar	Antonio Vivaldi	=
Archie Shepp: Blue Ballads	Archie Shepp	=
Archie Shepp: True Ballads	Archie Shepp	=
Archie Shepp: True Blue	Archie Shepp	=
 Archie Shepp: Blue Ballads (dsf) 	Archie Shepp Quartet	=
 Archie Shepp: True Ballads (dsf) 	Archie Shepp Quartet	=
Archie Shepp: True Blue (dsf)	Archie Shepp Quartet	=
Aretha Sings the Blues	Aretha Franklin	=
Accident and Insurgency	Arnie Somogyi's Ambulance	=
Beethoven Piano Sonatas	Artur Pizarro	=
Chopin Piano Sonatas	Artur Pizarro	=
Beethoven Piano Sonatas (HD)	Artur Pizarro	=
Strange Bird	Augie March	=
Agnes Baltsa Sings Rossini	Baltsa Agnes // Gioachino Rossini	=
Every Grain of Sand: Barb Jungr Sings Bob Dylan	Barb Jungr	=
Just like a woman - hymn to Nina	Barb Jungr	=
Love Me Tender	Barb Jungr	=
Magnetism	Ben Heit Quartet	=
Plays Ballads	Ben Webster	=
My Romance	Ben Webster	=
O Drive	Bic Runga	=
Drive Reput Dice	Ric Runan	



© Ideon Audio, August 2020 – absolute stream manual v.1

Database: here you get a full list of your music library (albums) sorted alphabetically by Albumartist (default). Clicking on relevant menu icon (top left) you can change the sorting field and get your library list sorted alphabetically by Album, Albumartist, Artist, or Genre.


The letters icon allows you to go to a specific letter of the alphabet in your library list.

Playlists: here you can see all playlists you have created and saved and, again, you can navigate through the letters icon selecting the desired letter of the alphabet.

Filesystem: here you get a complete view of your filesystem – all drives, disks, USB sticks, NAS, and / or whichever other form of storage you are using with your streamer. It follows a tree-structure, so you can easily go back and forth in your usual manner.

You can open any item by just clicking on it and move down the road until you get to the file level (track). The path appears at the top of your screen and is clickable, so you can navigate back and forth easily.

The little icon in the beginning of every row shows whether it is a directory (folder icon) or a track/song (musical note icon) row.



Filesystem

1/3-

Covergrid


ideon 📃 🔻


Database

Albumartist •

Playlist

Playlists





When you have selected a directory if you click on its menu icon (the three parallel lines at the end of the row) you get the following options:

Add to queue: add all the contents (tracks) of the directory to the end of the current queue (be careful, as depending on the directory these may be a lot!)

Replace queue: erases the current queue and replaces its contents with all the tracks of the selected directory

Add to playlist: choose a playlist -- or create a new one -- to which all the tracks of the selected directory will be added Add bookmark: bookmarks the selected directory for quick future reference/access. This might be very useful if you have large music libraries.

Update/Rescan directory: updates, meaning makes a new index of the directory. You can use this when you add new folders of tracks to the specific directory and you do not wish to update the whole library.

Clicking the **Home icon** gets you to the root directory.

Clicking on the **gear icon** – at the right side of the screen on the information row, allows you to choose the track information on the track being played. This information appears on the left pane below the track title (pic).

Clicking the **+ Icon** (the middle of the three top screen icons) lets you add all contents of the filesystem to the Queue or to a Playlist (be careful, contents tend to be huge!)

Clicking the **Bookmarks icon** (the right of the three top screen icons) you can browse and select a bookmarked directory for quick access

	audo			
Covergrid: here you can search, browse, sort and				
view all the Albums in your music library.	Database	Filesystem	m Covergrid	
	Q Albuma	artist 👻 Sea	arch	

The **Search bar** works as described above and the default search field is Albumartist. By clicking the arrow in the search bar menu, you can manually change the keyword search field to Album, Albumartist, Artist or Genre.

Database Playlists Filesystem	Covergrid	Library total: Tracks 2495 + Time 7 Days 8 Hrs 08 Min 21 S
Q Albumartist - Search		= Sort ▼ (≪ 1 > (+*




© Ideon Audio, August 2020 – absolute stream manual v.1

Due to continuous research, Ideon Audio reserves the right to change specifications without notice.

Album

The **Sort button** also works also as described above; by clicking on the arrow in the sort icon, you control how you wish to sort your Albums. We recommend using Albumartist.

Library total: Tracks 2495 • Time 7 Days 8 Hrs 08 Min 21 Sec



Important note for covergrid

The button on the far right (two arrows) is a toggle switch alternating between thumbnails and list view for your albums.

Search

The Search screen can be selected from the main bar of the application at the bottom of the screen. Here you can search your music library database.

Q Any Tag ▼ jsearch Title ▼ Artist Album Duration ♀	Database Tidal				
Title Artist Album Duration	Q Any Tag ▼ Search				
	Title	✓ Artist	Album	Duration	٥

In order to perform searches, you need to enter a keyword into the search bar. By default, the system will search any tag containing this keyword. By right-clicking on the arrow in the bar's search button, a drop-down menu appears; this allows you to define where the search is made – i.e. Filenames, Albums, Albumartists, Artists, Genre or Title (of track).

The search results appear in list form below the search bar.


By clicking the **+ button** at the right of the screen you add all search results (tracks) to the end of the current queue. If you use the arrow of the button you have the choice to either add the search results to the queue, or to a playing list.

Clicking on the **gear icon** – at the right side of the screen on the information row, allows you to choose the track information to be displayed.

Clicking on the mini menu on the right side of each track opens five options for any of the tracks and the albums appearing in the search results: **Play, Add to queue, Add after current playing song, Replace queue, Add to playlist, Song details** (available as an option only for tracks).

15

Ideon Main Menu



Add Stream: you can add the URL of a specific stream you want to play (provided you know its exact URL address), or just add it to a playlist for future access.

rro .	- Sonata No. 8 'Pathétique' in Ciminor Op. 13 Grave: Alleor ≡+ Add stream	o di molto o X
é e;	Stream URI http://uri.to/stream.mp3 Add to playlist	
	Cancel	Add


Create/Update library: as covered in previous section here you can create your music library the first time you start the system or update in later with new additions. Actually, the indexing of your albums and tracks takes place with this function.

When adding new albums or tracks, then use the Update Library function to index/include the newly added tracks to your library.

Use the Rescan library when you want to perform the process from the beginning i.e. building again your music library. You should do that in the case your files are corrupted, or something else has gone wrong.

Timer: you can set up a timer for auto music playback as well as, a kind of jukebox for the same reason.





Ö Timer	Adar Vizura - Sonsta No. 8 10 shiddianol in Cinitaer On. 13 Graws Allouro di malto o con bria Ō Timer					
Name	Enabled	Definition	Action			
0	Empty list					
New timer				Close		
no Sonatas (HD)		O Gemini	ani: Sonatas for Violoncell	o & Basso Contin		



© Ideon Audio, August 2020 – absolute stream manual v.1

General Settings

Important Notice

To ensure your changes to the settings take effect, you need to press on Apply. If you want to keep the changes you need to click on the Save button

Playback

	Δrtur Piz	zarro - Sonat	a No. 8 'Pathétiq	ue' in C minor Or	13 Grave: Al	learo di	molto e	con brid		
NI	Playback	General	Appearance	Advanced					×	
No Dp	Playback Random								Ο	
ro n Pia	Consume (remove track played)	from queue	after						0	inu ter
	Single						Off	On	Oneshot	
	Repeat track								0	
	Fade out (seco	onds)	0							
e; All	Replaygain					Off	Auto	Song	Album	
	Autoplay at st	artup							0	
	Jukebox									
	Jukebox mode	e					Off	Song	Album	
							ancel	Apply	Save	

Random (enabled/disabled): for random playback from your music library

Consume (enabled/disabled): if enabled, this function erases a track from the queue it has been played

Single: to play just one song at a time (or on shot)

Repeat track: (enabled/disabled): if enabled, the track is repeated

Fade out: you can define how many seconds of fade-out if you wish to have between tracks

Replay again: for auto replay or replaying a song or an album

Autoplay at start up (enabled/ disabled): if enabled, starts to play music automatically every time you switch on your device

Jukebox: you can enable Jukebox to play lists in this mode

Absolute Stream

General

	Playback General Appeara	ince Advanced	×
	Tags		
, op	Tags used in system	Artist, Album, Albumartist, Title, Track, Genre, Date	•
	Search function tags	Album, Albumartist, Artist, Genre, Title	-
	Library browsing tags	Album, Albumartist, Artist, Genre	-
	Statistics		
	Playback statistics		2
	Last played list count	20	· · · ·
	Playlists		
	Smart playlists		2
erto / Do	Generate smart playlist per	Genre	•
erto / Do erto / Do	Smart playlists prefix	ideonSmart	
erto / Do	Order	Disabled	•
	Update smart playlists (hours)	4	
	Scrobbler integration		
	Send love message		C
	Other features		
	Bookmarks		
	Timer		
	Lyrics		
	Booklet filename	booklet.pdf	
		Cancel Apply Sav	/e

Tags: there are three drop-down menus that you can use in order to select the tags that you wish to see when displaying information about your music, searching your tracks, or when you are just browsing through your library. Your music files need to contain a minimum of metadata in order to fully realize the potential of searching and tagging (see also an important notice about metadata at the end of this reference manual).

Statistics: (enabled/disabled): enabled, this compile statistics on your library and music playback. You can access these statistical data in the **About option** of the main Ideon menu and from some other sections of the app.

Playlists (enabled/disabled): if enabled you can basically configure and utilize Smart playlists based on parameters that you can set manually through the "Generate smart playlist per" option in this section. Smart playlists can be seen and accessed through the Library/ Playlists menu.

Scrobbler integration (enabled/ disabled): if enabled it lets Scrobbler users, i.e. online music audience, to scrobble their playback history.

Other features: options to enable/ disable self-explanatory items when available.

© Ideon Audio, August 2020 – absolute stream manual v.1

Α	D	D	e	a	ra	n	ce	1
/ ×		r	-		-		~~	

	Playback General Appeara	nce Advanced	×			
ne	Skin					
	Skin color	Default				
	Background color	#888 Preview				
	Highlight color	#28a745 Preview				
	Artwork					
	Album artwork	I	~			
	Name	folder, cover				
	Playing now size	250				
	Thumbnails	200				
Th	Background image		_			
Br Br	Album artwork	I	0			
Br	Notifications					
ł	On page notifications	1	0			
	Web notifications	I	0			
	Notifications are blocked					
	Chrome media session plugin support	I	~			
	Pagination					
	Items per page	100				

Skin color: select the desired skin color from a set menu or experiment with color codes yourself. You can preview before saving your selection

Artwork:

Playing now size: define in pixels the size of the album artwork in Playing now window/screen. Default is 250.

Thumbnails: define in pixels the size of the album artwork thumbnails, in Playing now and Library screens. Default is 200.

Background image

Album artwork: (enabled/disabled): if enabled, the artwork of current track playing appears in the background of the app.

Notifications: enable/disable

Pagination

It**ems per page:** define how may items you wish to see on a page, default is 100 as you can see in Playing now screen.

Advanced

Reset to factory default: resets the application to **Absolute Stream** factory settings.

Clear app cache and reload: this clears the applications cache. Please note that YOU WILL NEED TO RE-SCAN the Library after clearing the cache!

Playback General Appeara	ance Advanced	×
Advanced settings		
Reset to factory default	Reset	
Clear app cache and reload	Reload	
Clear artwork cache	Clear Crop	
Delete playlists	Delete empty playlists	Delete
		Cancel Apply Save

Clear artwork cache: this clears the artwork cache only. YOU WILL NEED TO RE-SCAN the Library afterwards.

Delete playlists: option to delete empty, smart or all playlists

Audio

Enable DoP

NAS

Audio Settings

DAC volume mode

Streaming

Update

Disabled

0

Ideon Settings

Audio

DAC volume mode: (enabled/disabled): if enabled it allows you to control the DAC's volume level provided that the DAC itself allows it.

Enable DoP: (enabled/disabled): should be enabled for DACs that do not support the transcode for DSD playback. It

basically converts everything into PCM format.

Important Notice

If your DAC does not support DSD playback, enable this option to play DSD files.

NAS Settings

In order to operate the **Absolute Stream** you need to configure your NAS (if you are using one) correctly right from the start.

To do this, you need to follow your NAS guidelines and this screen allows you to

Audio NAS Stream	ing Update		
Your NAS Settings			
Select type	None (not applicable)		
Changes here will cause a system re	None (not applicable)		
	Samba A (guest access)		
	Samba B (access with credentials)		
	NFS		

×

٥

make the required changes to the settings according to your preferred NAS protocol (such as Samba or NFS).

Streaming Services


Any of the following services can be rendered at an exceptionally high soundquality level by your Absolute Stream; all you need to do is enable the chosen service.

AirPlay: (enabled/disabled)

Roon: (enabled/disabled)

Spotify: (enabled/disabled)

Tidal: (enabled/disabled)





© Ideon Audio, August 2020 – absolute stream manual v.1

Update

Ideon Audio software update

Your Absolute Stream can and will be updated with future versions of the software, remotely. You can check for new updates here.

Vo-Vo Ma Patricia Zandor - "S Audio NAS Streaming	anas mu mathar tauaht ma" from Gransv maladiae, on 55, no 4 Update	×				
Ideon Audio software update Current version: Latest version: 						
Check for updates tr A	Check					
	Cancel Save					

21

SAFETY INSTRUCTIONS

- WARNING. TO REDUCE THE RISK OF FIRE OR ELECTRICAL SHOCK, DO NOT EXPOSE THIS DEVICE TO RAIN OR MOISTURE.
- Clean only with a dry cloth. Do not place flammable material on or underneath this device.
- Do not remove or bypass the ground pin on the end of the AC cord unless necessary to reduce hum from ground loops of connected equipment. Disconnecting the ground may cause RFI (radio frequency interference) to be induced into your playback setup. Removing or bypassing the ground pin on any electrical component is potentially dangerous and should be avoided for safety reasons.
- Protect the power cord from being walked on or pinched particularly at plugs, convenience receptacles, and the point where they exit from the apparatus. Unplug this apparatus during lightning storms or when unused for long periods of time.

Servicing

THERE ARE NO USER-SERVICEABLE PARTS INSIDE ANY IDEON AUDIO PRODUCT. PLEASE REFER ALL SERVICING TO QUALIFIED PERSONNEL.

Please contact your authorized dealer, distributor, or Ideon Audio if you have any questions not addressed in this reference document.



Warranty

Ideon Audio provides a 2-year manufacturer's warranty on all new Ideon Audio components.

The Ideon Audio **seven (7)** year and extended **Lifetime** Limited Warranty You can extend the standard 2-year manufacturer's warranty into a 7-year warranty by registering your product with us. To do that, you need to send us your Name, Address, tel., email and the proof of purchase in the form of a bill of sale, invoice (or copy thereof) from the Ideon Audio dealer or Distributor. For further detail please contact your dealer or refer to Ideon Audio's official site.

Furthermore, Ideon Audio also offers a Lifetime product warranty that can be purchased at 17,5% of the retail price for any of our products. Please coordinate with your dealer of local distributor for that.

The Ideon Audio limited warranty covers defects in the materials and workmanship in this product. Under the terms of this warranty we will repair the product free of charge (parts and labour) — or replace it where we deem that repair is not possible — for malfunction due to inherent defects in the materials or construction.

Ideon Audio has authorized distribution in many countries of the world. Warranty service should be obtained directly from the importing retailer or distributor from whom you



© Ideon Aud

© Ideon Audio, August 2020 – absolute stream manual v.1

purchased the product. In the unlikely event of service required beyond the capabilities of the importer, Ideon Audio undertakes to fulfill the conditions of the warranty. In case of malfunction please contact your dealer to arrange for service. If you have purchased the product directly from Ideon Audio, please contact us directly at info@ ideonaudio.com, quoting subject: fault and a short description of the issue. Please note that the product must be returned using original packaging only and accompanied by a written description of the issue, defect, or malfunction.

*Products covered by the extended, lifetime warranty.

- This specially extended warranty covers the lifetime of the product model.
- This warranty is transferable under condition that each new owner informs Ideon Audio importers, dealers, or Ideon Audio directly the device model, number, previous owner name & new owner name & address.
- In cases of obsolescence of materials or superseded technology, the product will be repaired using currently available materials and technology of
- equivalent performance characteristics, or better.
- Future proof": if Ideon Audio releases upgrades to, or improved versions of, the purchased product, these are made available to subscribers at cost of parts and materials only. Shipping to the service location is borne by the owner, Ideon Audio or its distributors / dealers pay for return shipping.
- location is borne by the owner, Ideon Audio or its distributors / dealers pay for return shipping.

*This warranty is voided in cases of

- Damage and /or malfunction caused by tampering or modifications to the product's original state, attempts to fix, or other alterations to the product by persons other than factory authorized service personnel.
- Damage and /or malfunction caused by improper use, abuse, or improper operation of the product.
- Failure to comply fully with Ideon Audio operating instructions.
- Damage to cables or attachments and cosmetic damage induced by use.
- Products obtained outside the network of authorized Ideon Audio dealers and resellers.

General Warranty Terms.

This Warranty is subject to the following conditions and limitations: The Warranty is void and inapplicable if the product has been used or handled other than in accordance with the instructions in this document, abused, or misused, damaged by accident or neglect or in being transported, or the defect is due to the product being repaired or tampered with by anyone other than Ideon Audio or an authorized Ideon Audio repair center.

- The product must be packaged and returned to Ideon Audio or an authorized Ideon Audio repair center by the customer at his or her sole expense in the original packing material. Ideon Audio will pay return freight of its choice for original purchasers.
- Returned product must be accompanied by a written description of the issue or the defect. Ideon Audio reserves the right to modify the design of its products without obligation to purchasers of previously manufactured products and to change the price or specifications of any product without notice or obligation to any person.
- In the event the product fails to meet this Warranty and the above conditions have been met, the purchaser's sole remedy under this Limited Warranty shall be to return the product to Ideon Audio or an

authorized Ideon Audio repair center where the defect will be repaired without charge for parts or labor.

- This warranty does not cover the cost of custom installation, customer instruction and setup adjustments.
- This warranty does not cover cosmetic damage or any damage due to accident, misuse, abuse, negligence or modification of, or to any part of the Product, without initial express consent from Ideon Audio. This warranty does not cover damage due to improper operation or maintenance, connection to improper voltage supply, or attempted repair by anyone other than a facility authorized by Ideon Audio to service the Product.



Enjoy the music, enjoy hi-definition in music!